



IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

2634

JPW

In patent application of
Gary Q. Jin

Serial No. 09/739,979

Group Art Unit: 2634

Filed: December 20, 2000

Examiner: Eva Y. ZHENG

For: DMT Bit Allocation with Imperfect TEQ

Customer No. 33361

Confirmation No. 3732

The Honorable Commissioner of
Patents and Trademarks
P.O. Box 1450
Alexandria, VA 22313-1450
U.S.A.

Sir:

In response to the office action mailed June 7, 2004, and to substantiate applicant's claim to priority, I enclose a certified copy of British patent application No. 9930399.2 filed December 23, 1999.


Respectfully submitted,

Thomas Adams, Reg. No. 31,078

Adams Patent & Trademark Agency
Box 11100, Station H
Ottawa, Ontario
Canada K2H 7T8

Docket No. AP1098US

Tel: (613) 254 9111



THIS PAGE BLANK (USPTO)



INVESTOR IN PEOPLE

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

The undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in the certificate and any accompanying documents has re-registered under the Companies Act 1985 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in the certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.

Signed

Dated

8 January 2001

**CERTIFIED COPY OF
PRIORITY DOCUMENT**

THIS PAGE BLANK (USPTO)

Patents Form 1/77

Patent
(Rule 1977)**The
Patent
Office**

THE PATENT OFFICE

A

23 DEC 1999

Request for grant of a patent FAX


(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

23DEC99 E501511-1 D01070
P01/7700 0.00-9930399 The Patent OfficeCardiff Road
Newport
Gwent NP9 1RH

| | | | |
|----|--|-------------------------------|---|
| 1. | Your reference | | |
| | P2533.P3/RAM | | |
| 2. | 9930399.2 | | 23 DEC 1999 |
| 3. | Full name, address and postcode of the or of each applicant (<i>underline all surnames</i>) Patents ADP number (<i>if you know it</i>) If the applicant is a corporate body, give the country/state of its incorporation | | |
| | Mitel Corporation 350 Legget Drive Kanata Ontario Canada K2K 2W7 Canada 7554298001 | | |
| 4. | Title of the invention | | |
| | DMT BIT ALLOCATION WITH IMPERFECT TEQ | | |
| 5. | Name of your agent (<i>if you have one</i>) "Address for service" in the United Kingdom to which all correspondence should be sent (<i>including the postcode</i>) Patents ADP number (<i>if you know it</i>) | | |
| | Dummett Copp 25 The Square Martlesham Heath Ipswich IP5 3SL 6379001 | | |
| 6. | If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (<i>if you know it</i>) the or each application number | Country | Priority application number (<i>if you know it</i>) Date of filing (<i>day / month / year</i>) |
| 7. | If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application | Number of earlier application | Date of filing (<i>day / month / year</i>) |
| 8. | Is a statement of inventorship and of right to grant of a patent required in support of this request? (<i>Answer 'Yes' if:</i> a) any applicant named in part 3 is not an inventor, or b) there is an inventor who is not named as an applicant, or c) any named applicant is a corporate body. See note (d)) | | |
| | Yes | | |

Patents Form 1/77

Patents Form 1/77



9. Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document.

Continuation sheets of this form

Description 7 /
 Claim(s) 4 /
 Abstract 1 /
 Drawing(s) 2 /

10. If you are also filing any of the following, state how many against each item.

Priority documents

Translation of priority documents

Statement of inventorship and right to grant of a patent (Patents Form 7/77) 1

Request for preliminary examination and search (Patents Form 9/77) 1

Request for substantive examination (Patents Form 10/77) 1

Any other documents (please specify)

11. I/Wc request the grant of a patent on the basis of this application.

Dummett Copp

Signature

Date

23 December 1999

12. Name and daytime telephone number of person to contact in the United Kingdom

Robert McLean - 01473 660600

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- a) If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
- b) Write your answers in capital letters using black ink or you may type them.
- c) If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- d) If you have answered 'Yes' Patents Form 7/77 will need to be filed.
- e) Once you have filled in the form you must remember to sign and date it.
- f) For details of the fee and ways to pay please contact the Patent Office.

Patents Form 1/77

Patents Form 7/77

Patent
(Rule 15)23 DEC 1999
RECEIVED BY **The Patent Office****Statement of inventorship and of
right to grant of a patent****The Patent Office**Cardiff Road
Newport
Gwent NP9 1RH

| | | |
|----|---|---------------------------------------|
| 1. | Your reference | P2533.P3/RAM |
| 2. | Patc (if any) | 9930399.2 |
| 3. | Full name of the or of each applicant | MITEL CORPORATION |
| 4. | Title of the invention | DMT BIT ALLOCATION WITH IMPERFECT TEQ |
| 5. | State how the applicant(s) derived the right from the inventor(s) to be granted a patent | By virtue of employment |
| 6. | How many, if any, additional Patents Forms 7/77 are attached to this form (see note (c)) | |
| 7. | I/We believe that the person(s) named over the page (and on any extra copies of this form) is/are the inventor(s) of the invention which the above patent application relates to. | |
| | Signature | Date |
| | Dummett Copp | 23 December 1999 |
| 8. | Name and daytime telephone number of person to contact in the United Kingdom | Robert McLean 01473 660600 |

Notes

- a) If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
- b) Write your answers in capital letters using black ink or you may type them.
- c) If there are more than three inventors, please write the names and addresses of the other inventors on the back of another Patents Form 7/77 and attach it to this form.
- d) When an application does not declare any priority, or declares priority from an earlier UK application, you must provide enough copies of this form so that the Patent Office can send one to each inventor who is not an applicant.
- e) Once you have filled in the form you must remember to sign and date it.

Patents Form 7/77

Patents Form 7/77



THE PATENT OFFICE
A
23 DEC 1999
RECEIVED BY FAX

Enter the full name, address and postcodes of the inventors in the boxes and underline the surnames

Gary Qu Jin
51 Liston Crescent
Kanata
Ontario
K2L 2W3
Canada

7310188001

Patents ADP number (if you know it):

Patents ADP number (if you know it):

Reminder

Have you signed the form?

Patents ADP number (if you know it):

Patents Form 7/77

DUPLICATE

- 1 -

DMT BIT ALLOCATION WITH IMPERFECT TEQField of the Invention

5 This invention relates to a Digital Subscriber Line (DSL) transmission systems employing a Discreet Multitone (DMT) modulation scheme and, more particularly, to a system and method for optimizing bit allocation in such an implementation.

Background

10 The expanding use of Internet services, electronic mail, file transfer and other home-office applications, continues to drive the need for higher bandwidth access to the home and small business operations. The Digital Subscriber Line (DSL) technology, including Asymmetrical Digital Subscriber Line (ADSL), has provided an effective mechanism to make use of
15 existing copper access loops and to significantly increase transmission speeds while permitting parallel usage of telephone and Internet services.

The Discreet Multitone (DMT) modulation technique is a particularly suitable way of implementing DSL in order to provide high speed and efficient use of existing bandwidth. In
20 DMT, multiple narrow bandwidth carriers all transmit at once in parallel and each carry a small fraction of the total information. The discreet bands or subchannels are independently modulated with a carrier frequency corresponding to the center frequency of the carriers and are processed in parallel. For example, in DMT, the bandwidth may be divided into 256 sub-carriers, each with a 4 kHz bandwidth. Multi-carrier modulation requires orthogonality
25 between all the sub-carriers and a Fast Fourier Transform (FFT) is a convenient method of achieving this modulation. At low frequencies, where copper wire attenuation is low and signal to noise ratio (SNR) is good, it is common to use a high bit rate, but at higher frequencies when unfavourable line conditions exist, modulation is relaxed to accommodate lower signal to noise ratio. Impulse noise which may be generated by electrical appliances,
30 lightning or with a phone going off hook or ringing, is wideband in frequency and narrow in

P2533P3
23 December 1999

- 2 -

time so it is spread over many DMT subchannels and its influence over any subchannel is relatively small. Nonetheless, the line impulse response can result in symbol distortion at the receiver. In order to offset the line impulse response, it is known to insert a cyclic prefix (M) in the time domain samples. The cyclic prefix between symbols tends to reduce inter-symbol interference. Frequently, however, the line impulse response will last longer than the typical cyclic prefix time samples and, to address this, it is known to implement a time domain channel equalizer (TEQ) algorithm. The TEQ algorithm, which applies a Fast Fourier Transform, attempts to shorten the line impulse response into M time samples. However, the response can never be exactly the finite duration of the M sample regardless of the kind of TEQ algorithm implemented. As a result, there is always channel leakage outside the M samples which causes symbol distortion or inter-channel interference at the receiver. Although the interference level is mostly very small, the interference is not evenly distributed about the channels and some channels may experience much higher interference which will cause receiver data error. In the present invention, the cross-channel interference with imperfect or inadequate TEQ is estimated and the transmitted data allocation is based on the interference levels. For example, more bits are provided to the channel with less interference, and less bits are provided to the channel with high interference. This controls the bit error rate into the desired level.

20 Summary of the Invention

The present invention provides a method of measuring the cross-channel interference in a DMT system in which line impulse influence exists after a TEQ algorithm.

25 The present invention also provides a simple, optimum implementation for bit allocation in a DMT scheme as used in a DSL application.

Therefore, in accordance with a first aspect of the present invention there is provided a method of determining interference between channels in a digital subscriber line (DSL) transmission system employing discrete multitone (DMT) modulation comprising:

P2533P3
23 December 1999

- 3 -

determining a peak power mask level per channel (P_k);
obtaining a channel impulse value ($h(n)$) after implementation of a time equalization (TEQ)
algorithm; and
multiplying the per channel power mask level and a residual impulse spectrum to obtain a
5 cross-channel interference level.

In accordance with a second aspect of the present invention there is provided a method of
estimating cross-channel interference ($I(k)$) in a discrete multitone (DMT) communication
system implemented in a digital subscriber line (DSL) application, the DMT system
10 employing inter-symbol cyclic prefix (M) and time equalization (TEQ), the method
comprising:

- a) measuring a total channel impulse response ($h(n)$) value remaining after TEQ;
- b) zeroing M main coefficients from $h(n)$;
- c) performing fast fourier transform (FFT) analysis on the result of step b); and
- 15 d) obtaining $I(k)$ by multiplying the result of step c) with a measured maximum power per
channel value.

In accordance with a further aspect of the present invention there is provided a method of
allocating bits per channel in a DMT communication system implemented in a DSL
20 application, the system employing inter-symbol cyclic prefix and time equalization, the
method comprising:

performing a first bit allocation algorithm to obtain a first bit per channel value and a first
power per channel level;

obtaining a cross-channel interference value based on a measured impulse response;

25 obtaining a noise value by adding the cross-channel interference value to an interference
noise value;

obtaining a second power mask per channel level based on a pre-calculated power per
channel level; and

30 implementing a second bit allocation algorithm utilizing the noise value, a signal to noise
ratio and the second power mask per channel level to obtain a final bit per channel allocation.

P2533P3

23 December 1999

- 4 -

Brief Description of the Drawings

The invention will now be described by way of example, with reference to the accompanying drawings, in which:

Fig. 1 shows the frequency and time relationship in a discrete multitone (DMT) implementation;

Fig. 2 is a block diagram of a basic DMT transmitter;

Fig. 3 is a basic block diagram of a DMT receiver;

Fig. 4 shows at a high level the bit allocation process; and

Fig. 5 illustrates at a high level the interference measurement process.

Detailed Description of the Invention

As discussed previously, DMT operates in the frequency domain. Each DMT subchannel (there are many being communicated in parallel) lasts a long time but operates in a narrow frequency band of the total bandwidth. As shown in Fig. 1, the total carrier frequency is divided into many narrow bands, and each is modulated with information in the time domain. Bits are allocated to each subchannel for transmission and at the receiver, the bits in each subchannel are demodulated to retrieve the communicated information.

In the DMT based DSL system N point FFT is used to transform N frequency subchannel carriers having quadrature amplitude modulation (QAM) modulated thereon into N point time domain samples. Thus in Fig. 2, input data is provided to a serial to parallel encoder. The output has N QAM symbols imparted thereto and, following the Inverse Fast Fourier Transform (IFFT) 12, the data is broken into time domain samples and, following the parallel to serial converter 14 the time domain signal may be passed through a digital to analogue converter (not shown) and on to the output line. Typically a cyclic prefix (M) 16 is inserted into the time domain signal prior to transmission.

P2533P3
23 December 1999

- 5 -

The received signal as shown in Fig. 3, is passed through an A to D converter (not shown). Typically, the cyclic prefix M has a smaller value than N for minimum redundancy. Because most line impulse responses last much longer than M time samples, a time domain channel equalizer (TEQ) 18 is required. There are several TEQ algorithms available that are used to shorten the channel into M time samples. However, the channel can never have an exactly finite duration with only M samples, no matter what kind of TEQ algorithm is applied. As a result, there is always channel leakage outside the M samples which will cause symbol distortion or inter-channel interference at the receiver. Although the interference level is usually very small, the interference is not evenly distributed between the channels, and some channels may experience much higher interference levels which, in turn, will cause receiver data error.

Fig. 4 shows pictorially the bit allocation scheme, including cross-channel interference measurement according to the present invention. Typically, the bit allocation algorithms use the following information to decide how many bits should be transmitted on each channel: power mask or maximum transmission power at each channel; noise level including near end cross talk (NEXT) and far end cross talk (FEXT), the signal to noise ratio (SNR) requirements for bit transmission and the channel impulse response which gives channel attenuation for each channel. The output of the bit allocation algorithm provides: the number of bits to be transmitted per channel and the corresponding transmitting power for each channel.

In Fig. 4, the first bit allocation algorithm 20 takes inputs $N(k)$ which is the measured noise power for each channel; $P(k)$ which is the power mask level which limits maximum transmission power for each channel; and $SNR(bn)$ which is the signal to noise ratio requirement when bn bits are transmitted at the given channel. As shown in Fig. 4, the outputs of the first bit algorithm are $b(k)$ which is the number of bits to be transmitted at channel k in accordance with the bit allocation algorithm 20 and $P_x(k)$ which is the transmission power for channel k .

P2533P3
23 December 1999

- 6 -

The interference measurement block 22 of Fig. 4 measures the cross-channel interference level $I(k)$ based on the total channel impulse response $h(n)$ after the time equalization (TEQ) algorithm and the transmission power input $P(k)$ from the first allocation algorithm. The interference $I(k)$ which is the statistically combined interference to channel k from all other channels will be added to the measured noise level $V(k)$ and the result $V_1(k)$ becomes the modified noise power input which is provided to the second bit allocation algorithm 24. The interference block 22 also outputs the new power mask $P_1(k)$ for the second bit allocation algorithm 24. The reason for a new power mask function is that the cross-channel interference $I(k)$ is signal dependent. Since the total noise level increases with cross-channel interference noise being added, the signal transmitting power will be increased as well. Consequently, the cross-channel interference $I(k)$ will be increased which otherwise would result in a repeating loop. The interference block 22 calculates the new power mask $P_1(k)$ based on the pre-calculated transmitter power $P_x(k)$ and the maximum power transmitted will be fixed at $P_1(k)$. The calculated interference is based on the maximum possible transmission power $P_1(k)$. With the new power mask $P_1(k)$ and noise power $V_1(k)$, the second bit allocation algorithm is implemented to obtain the final bit allocation $b_1(k)$ and its corresponding transmitting power $P_{x1}(k)$ which takes into account the aforementioned cross-channel interference.

One way to determine the new power mask function is described as follows:

Let $P_{max} = \max (P_x(k))$, then we have

$$P_1(k) = \begin{cases} P_{max}, & P(k) \geq P_{max} \\ P(k), & P(k) < P_{max} \end{cases}$$

The above equation means that P_{max} is chosen as the new maximum transmission power for all channels unless it is above the original mask power, in which case the original mask power $P(k)$ is retained. In theory, with the newly calculated mask power, it is possible to calculate statistic interference level in all channels. However, the precise calculation is still a very complicated procedure that involves the computation of each channel interference from

P2533P3
23 December 1999

- 7 -

all other channels. Fig. 5 shows a simple approximate upbound or upper limit for the cross-channel interference with given total channel impulse response $h(n)$ after TEQ.

As mentioned before, with M point cyclic prefix being added in the transmit signal, there will be no interference if the total channel response $h(n)$ is of finite length lasting only M sample points. The block "zeroing M coefficients" 26 in Fig. 5 sets those M coefficients to zeros and the remaining coefficients in $h(n)$ are then the source of the inter-channel interference. Taking Fourier transform in FFT block 28 of the remaining channel response and multiplying them at multiplier 30 with $P_1(k)$ gives out the upbound for the cross-channel interference $I(k)$.

To get the interference level, it is possible to use either $I(k)$ or the envelop of $I(k)$, or some other modified form of $I(k)$. $P_1(K)$ can also be modified based on $P_x(k)$ and $P(k)$. In the $P_1(k)$ calculation, P_{\max} can be replaced with a local maximum of $P_x(k)$, such that $P_{\max}(k) = \max_{k1}(P_x(k+k1))$, for $-C < k1 < C$, where C is predetermined value to decide the neighboring area around K . If $P_1(k)$ is chosen such that $P_1(k) = \min([SNR(\max(bn))][\max(V(k))], \max(P(k))]$, the first bit allocation in Fig. 4 becomes unnecessary. In this way, one half the computation for bit allocation is saved by running it only once and $P_1(k)$ becomes a constant which is the maximum potential transmitted power at each channel.

P2533P3
23 December 1999

- 8 -

Claims:

1. A method of determining interference between channels in a Digital Subscriber Line (DSL) transmission system employing Discrete Multitone (DMT) modulation comprising:
determining a power mask level per channel $P(k)$;
obtaining a channel impulse value $h(n)$ after implementation of a time equalization (TEQ) algorithm; and
multiplying the per channel power mask level and a residual impulse spectrum to obtain a cross channel interference ($I(k)$) level.
2. The method according to claim 1 wherein a Fast Fourier Transform (FFT) is employed to obtain said residual impulse spectrum.
3. A method of estimating cross channel interference $I(k)$ in a Discrete Multitone (DMT) communication system implemented in a Digital Subscriber Line (DSL) application, said DMT system employing inter-symbol cyclic prefix (M) and Time Equalization (TEQ), the method comprising:
a) measuring a total channel impulse response $h(n)$ after TEQ;
b) zeroing M main coefficients from $h(n)$;
c) performing Fast Fourier Transform (FFT) analysis on the result of step b); and
d) obtaining $I(k)$ by multiplying the result of step c) with a maximum power per channel value.
4. A method of allocating bits per channel in a DMT communication system implemented in a DSL application, said system employing inter-symbol cyclic prefix and Time Equalization, said method comprising:
performing a first bit allocation algorithm to obtain a first bit per channel value and a first power per channel level;

P2533P3
23 December 1999

- 9 -

obtaining a cross channel interference value based on a measured impulse response;
obtaining a noise value by adding the cross channel interference value to an interference noise value;
obtaining a second power mask per channel based on a pre-calculated power per channel level; and
implementing a second bit allocation algorithm utilizing said noise value, a signal to noise ratio and said second power mask per channel level to obtain a final bit per channel allocation.

5. The method according to claim 5 wherein a second power per channel level is derived by said second bit allocation algorithm.

6. A system for determining interference between channels in a Digital Subscriber Line (DSL) transmission system employing Discrete Multitone (DMT) modulation comprising:
means to determine a power mask level per channel $P(k)$;
means to obtain a channel impulse value $h(n)$ after implementation of a time equalization (TEQ) algorithm; and
a multiplier to multiply the per channel power mask level and a residual impulse spectrum to obtain a cross channel interference ($I(k)$) level.

7. A system for estimating cross channel interference $I(k)$ in a Discrete Multitone (DMT) communication system implemented in a Digital Subscriber Line (DSL) application, said DMT system employing inter-symbol cyclic prefix (M) and Time Equalization (TEQ), the system comprising:

- a) measurement means to measure a total channel impulse response $h(n)$ after TEQ;
- b) means to zero M main coefficients from $h(n)$;
- c) means to perform Fast Fourier Transform (FFT) analysis on the result of step b); and
- d) means to obtain $I(k)$ by multiplying the result of step c) with a maximum power per channel value.

P2533P3
23 December 1999

- 10 -

8. A system for allocating bits per channel in a DMT communication scheme implemented in a DSL application employing inter-symbol cyclic prefix and Time Equalization, said system comprising;
- 5 means for performing a first bit allocation algorithm to obtain a first bit per channel value and a first power per channel level;
- means for obtaining a cross channel interference value based on a measured impulse response;
- means for obtaining a noise value by adding the cross channel interference value to an
- 10 interference noise value;
- means for obtaining a second power mask per channel based on a pre-calculated power per channel level; and
- means for implementing a second bit allocation algorithm utilizing said noise value, a signal
- 15 to noise ratio and said second power mask per channel level to obtain a final bit per channel allocation.
9. A method of determining interference between channels in a Digital Subscriber Line (DSL) transmission system
- 20 employing Discrete Multitone (DMT) modulation, substantially as herein described, with reference to the accompanying drawings.
10. A method of estimating cross channel interference $I(k)$ in a Discrete Multitone (DTM) communication system
- 25 implemented in a Digital Subscriber Line (DSL) application, substantially as herein described, with reference to the accompanying drawings.
11. A method of allocating bits per channel in a Discrete Multitone (DMT) communication system implemented in a
- 30 Digital Subscriber Line (DSL) application, substantially as herein described, with reference to the accompanying drawings.
- 35

P2533P3
23 December 1999

- 11 -

12. A system for determining interference between channels in a Digital Subscriber Line (DSL) transmission system employing Discrete Multitone (DMT) modulation, substantially as herein described, with reference to the accompanying drawings.

13. A system for estimating cross channel interference $I(k)$ in a Discrete Multitone (DTM) communication system implemented in a Digital Subscriber Line (DSL) application, substantially as herein described, with reference to the accompanying drawings.

14. A system for allocating bits per channel in a Discrete Multitone (DMT) communication system implemented in a Digital Subscriber Line (DSL) application, substantially as herein described, with reference to the accompanying drawings.

P2533P3
23 December 1999

- 12 -

Abstract

DMT Bit Allocation with Imperfect TEQ

5 The invention relates to a method of determining cross
channel interference in a Discrete Multitone (DMT)
implementation of a Digital Subscriber Line (DSL) system.
The cross channel interference is determined utilizing a
residual impulse spectrum after implementation of a Time
10 Equalization (TEQ) algorithm. In one application the cross
channel interference value is used in a bit allocation
algorithm to improve error rate such that more bits are
allocated to the channels with low interference and fewer
bits are allocated to those channels having high
15 interference. In this application the bit allocation
algorithm is run twice, once before the interference
measurement and once after.

F2533P3
23 December 1999

1/2




FIGURE 1




FIGURE 2




FIGURE 3

NOT TO BE AMENDED

THIS PAGE BLANK (USPTO)

2/2




FIGURE 4




FIGURE 5

NOT TO BE AMENDED

TOTAL P.21

THIS PAGE BLANK (USPTO)